

- High brightness display: 1~999999
- High stability, non-flammable case (PC), high safety
- Reset by external control terminal available
- A/A-1/A-2/A-3/B/B-1/D/E/Z/TON/TOFF/F-1 relay output mode selectable
- 2 alarms programmable / RS-485 communication optional
(The above option can exist together)



SPECIFICATION


- | | | | |
|-----------------------|---|----------------------------|--|
| ◆ Display Screen: | High brightness LED | ◆ Relay Output Mode: | A/A-1/A-2/A-3/B/B-1/D/E/Z/TON/TOFF/F-1 |
| ◆ Display Range: | 999.999S 9999.99S 99999.9S 999999S 9999M99S 99999.9M 999999M 9999H99M 99999.9H 999999H | ◆ Communication: | RS-485 Modbus ASCII mode |
| ◆ Parameters Setting: | Push buttons | ◆ Baud Rate: | 57600 / 38400 / 19200 / 9600 4800 / 2400 / 1200 bps |
| ◆ Back Up Memory: | EEPROM | ◆ Parity Check: | none / odd / even |
| ◆ Relay Contact: | AC 250V / 3A; DC 30V / 5A | ◆ Temperature Coefficient: | 100ppm / °C (0~60°C) |
| | | ◆ Operating Temperature: | 0~60°C |
| | | ◆ Operating Humidity: | 35~85% RH (non-condensing) |
| | | ◆ Storage Temperature: | -10~70°C |
| | | ◆ Storage Humidity: | 35~85% RH (non-condensing) |
| | | ◆ Power Supply: | AC 100~240V; DC 24V |
| | | ◆ Power Consumption: | 5VA |
| | | ◆ Surge Test: | 1.5KVac / 1min (Input / Power) |

ORDER INFORMATION

L482T - [Code 1] [Code 2] - [Code 3]

| Code1 | Aux. Power | Code2 | Alarm Output | Code3 | RS-485 |
|-------|-------------|-------|--------------|-------|--------|
| A | AC 100-240V | R2 | 2 Relay | N | None |
| C | DC 24V | | | Y | YES |

WIRING CONNECTION



DIMENSION

