H2S LCD SENSOR

DC110-H25

- Capable of measuring H2S concentration.
- Emits audible and visual alarm signals when the H2S concentration exceeds the preset alarm threshold.
- Highly responsive with strong anti-interference capability.
- Features a unique compensation algorithm and multi-point standard gas calibration.
- Characterized by high repeatability and excellent stability.
- Uses remote infrared control technology, allowing parameter adjustments without disassembly.
- Equipped with a high-quality LCD screen for direct value display.
- Operates on a wide DC voltage range of 10–30V, compatible with various DC power supplies.
- Wall-mounted enclosure for easy installation.

Infrared Receiver Infrared Receiver Operation Fault Alarm

SPECIFICATIONS -

◆ Power Supply★ Average Power∴ 10~30Vdc∴ 0.6W (24Vdc)

Consumption

◆ Operating Temperature : -10~50°C

♦ Output Signal : 4-20mA/ 0-10V/ 485 output

♦ Repeatability : ≤2%

♦ Stability : ≤2% of signal value per month
 ♦ Operating Humidity : 15~90%RH non-condensing

◆ Operating Pressure
 ◆ Warm-up Time
 ◆ Resolution
 : 90~110kPa
 : ≥5min
 : 1ppm

♦ Accuracy : ±2ppm or±10%

Zero Drift : ±5ppm Response Time : ≤35s

- Gas concentration display
- ② Gas unit display
- 3 Cyclic display of Add (address) and Baud (baud rate)
- 4 In item 3, "Add" indicates the address code, and "Baud" indicates the baud rate
- (5) Whether RS-485 communication is successful; once communication is successful, the display remains for 60 seconds

ORDER INFORMATION

DC110-H2S- Code1 - Code2

Code1	Measurement Range	
100P	100ppm	
Code2	Output Signal	
V Code2	Output Signal 0~10V	
V Y		

WIRING CONNECTION

Comm.	Position	Description
Power	1	Power+(10-30Vdc)
	2	Power-(GND)
Comm.	3	Signal+(485-A)
	4	Signal-(485-B)

Analog	Position	Description
Power	1	Power+(10-30Vdc)
	2	Power-(GND)
Output	3	Signal+(AO)
	4	Signal-(GND)

1 2 3 4

Wide voltage power input: 10–30V is supported.

*Note: 0–10V output requires 24V power supply.

*When connecting RS-485 signal lines, make sure A and B lines are not reversed.

Device addresses on the same bus must not conflict.

DIMENSIONS (mm)





