DCbox

HALL CURRENT SENSOR



- Efficient, beneficial, and low cost.
- Measurement frequency range: DC~20KHz, low power consumption 10mA.
- Measurement input without loss; Strong anti-interference ability.
- Lightweight structure for easy installation. Opening size 64*16mm.
- DTM-S64 is a current comparator made using the Hall effect principle, suitable for measuring direct current.
- Open structure design, convenient for continuous electrical installation, with screw fixation design at the opening and closing parts, safe and firm to prevent detachment.

At DC, V outputs 0-4Vdc; Output A: 4-20mAdc

Corresponding input current range In

<±1.0% F.S. (@ 25°C)

SPECIFICATION

- Output signal:
- Precision:
- Working power supply:
- Measurement frequency range:
- Zero offset voltage:
- Temperature drift:
- ◆ Linearity:
- Reaction time:
- Working temperature:
- ◆ Storage temperature:
- Current consumption:
- ◆ Load resistance:
- Weight:
- ◆ Shell material:

Model

DTM-S64-300

DTM-S64-400

DTM-S64-500

DTM-S64-600

DC12V(±5%) DC~20KHz ◆ Insulation and withstand voltage: 2.5KV effective value/ 60Hz/ 1 min (between input and output circuits) <+10mV ±1mV/ °C <±1% F.S < 5µSec -10°C~+85°C -25°C~+85°C <25mA >10KΩ 410g(square)

Maximum measuring range

75A

150A

300A

450A

Flame retardant PBT material, grade: UL94-V0

Opening size

64*16mm

64*16mm

64*16mm

64*16mm

64*16mm

64*16mm

DIMENSION





DTM-S64-1000 600A 400A DTM-S64-2000 750A 500A **ORDER INFORMATION**

Primary side rated current

50A

100A

200A

300A

DTM- Code1 64 - Code2 - Code3

Со	de1	Туре	Code2	Measure Range	Code2	Measure Range	Code3	Output Signal
ļ	S	Square	300	DC0~300A	600	DC0~600A	V	0~4Vdc
			400	DC0~400A	1000	DC0~1000A	А	4~20mAdc
			500	DC0~500A	2000	DC/AC 0~2000A		

WORKING PRINCIPLE



The magnetic flux generated by the primary current IP is concentrated in the magnetic flux, detection at the air gap using a Hall comparator.

The output of the Hall device is processed at the sensor output end can accurately reflect the current changes on the primary side.